

# INSTALLATION INSTRUCTIONS

## LED Canopy Light



### CAUTIONS

#### READ AND FOLLOW ALL SAFETY INSTRUCTIONS

1. DANGER- Risk of shock- Disconnect power before installation.
2. This luminaire must be installed in accordance with the NEC or your local electrical code.
3. Suitable for wet location and operation in ambient not exceeding 40°C
4. Min 75°C supply conductors.
5. Products are not intended for use in environments containing airborne corrosive airborne corrosiveagents such as chemical solvents, cleaners,or cutting fluids.
- 6.This luminaire is rated for 120-277Vac 50/60Hz only.
7. Replace the Lens if damaged



### Surface Mount

<p>Labels: Mounting Plate, Screw</p>	<p>Labels: Junction Box</p>	<ol style="list-style-type: none"> <li>1. Remove the mounting Plate by removing the 1 screws</li> <li>2. Fasten the mounting plate to the junction box using the screws supplied with the Junction box.</li> <li>3. Complete the wiring to the power source and ground,Using customer supplied 90°C minimum rated wireconnectors,make the following electrical connections in the mounting box or junction box:             <ol style="list-style-type: none"> <li>a. Connect the black fixture lead to the voltage supply lead</li> <li>b. Connect the white fixture lead to the neutral supply lead</li> <li>c. Connect the ground lead to the supply ground lead.</li> </ol> </li> <li>4. Replace Lighting housing by reversing procedure used to remove it.</li> </ol>
<p>Labels: Make Connectio</p>	<p>Labels: Junction Box, Ceiling, Luminaire</p>	

### Conduit Mount

<p>Labels: Mounting Plate, Screw</p>	<p>Labels: Junction Box, Ceiling, Make Connection</p>	<ol style="list-style-type: none"> <li>1. Remove the mounting Plate by removing the 1 screws</li> <li>2. Complete the wiring to the power source and ground, Using customer supplied 90°C minimum rated wire connectors,make the following electrical connections in the mounting box or junction box:             <ol style="list-style-type: none"> <li>a. Connect the black fixture lead to the voltage supply lead</li> <li>b. Connect the white fixture lead to the neutral supply lead</li> <li>c. Connect the ground lead to the supply ground lead.</li> </ol> </li> <li>3.Tighten the conduit into luminaire</li> </ol>
<p>Labels: Junction Box, Ceiling</p>	<p>Labels: Junction Box, Ceiling, Luminaire</p>	